N-Channel Enhancement-Mode Vertical DMOS FETs

Ordering Information

BV_{DSS} / BV_{DGS}	$R_{DS(ON)}$ (max)	$V_{GS(th)}$ (max)	$I_{D(ON)}$ (min)	Order Number / Package	
				TO-243AA*	Die†
100V	1.5Ω	2.0V	3.0A	TN2510N8	TN2510ND

* Same as SOT-89. Product supplied on 2000 piece carrier tape reels.
† MIL visual screening available.

Product marking for TO-243AA:

TN5A✳

Where ✳ = 2-week alpha date code

Features

- ❑ Low threshold —2.0V max.
- ❑ High input impedance
- ❑ Low input capacitance — 125pF max.
- ❑ Fast switching speeds
- ❑ Low on resistance
- ❑ Free from secondary breakdown
- ❑ Low input and output leakage
- ❑ Complementary N- and P-channel devices

Applications

- ❑ Logic level interfaces – ideal for TTL and CMOS
- ❑ Solid state relays
- ❑ Battery operated systems
- ❑ Photo voltaic drives
- ❑ Analog switches
- ❑ General purpose line drivers
- ❑ Telecom switches

Absolute Maximum Ratings

Drain-to-Source Voltage	BV_{DSS}
Drain-to-Gate Voltage	BV_{DGS}
Gate-to-Source Voltage	± 20V
Operating and Storage Temperature	-55°C to +150°C
Soldering Temperature*	300°C

* Distance of 1.6 mm from case for 10 seconds.

Low Threshold DMOS Technology

These low threshold enhancement-mode (normally-off) transistors utilize a vertical DMOS structure and Supertex's well-proven silicon-gate manufacturing process. This combination produces devices with the power handling capabilities of bipolar transistors and with the high input impedance and positive temperature coefficient inherent in MOS devices. Characteristic of all MOS structures, these devices are free from thermal runaway and thermally-induced secondary breakdown.

Supertex's vertical DMOS FETs are ideally suited to a wide range of switching and amplifying applications where very low threshold voltage, high breakdown voltage, high input impedance, low input capacitance, and fast switching speeds are desired.

Package Option



TO-243AA
(SOT-89)

Note: See Package Outline section for dimensions.

11/12/01

Thermal Characteristics

Package	I_D (continuous)*	I_D (pulsed)	Power Dissipation @ T_A = 25°C	θ_{jc} °C/W	θ_{ja} °C/W	I_{DR}*	I_{DRM}
TO-243AA	0.73A	5.0A	1.6W†	15	78†	0.73A	5.0A

* I_D (continuous) is limited by max rated T_j.
† Mounted on FR5 board, 25mm x 25mm x 1.57mm. Significant P_D increase possible on ceramic substrate.

Electrical Characteristics (@ 25°C unless otherwise specified)

Symbol	Parameter	Min	Typ	Max	Unit	Conditions
BV_{DSS}	Drain-to-Source Breakdown Voltage	100			V	V_{GS} = 0V, I_D = 2mA
$V_{GS(th)}$	Gate Threshold Voltage	0.6		2.0	V	V_{GS} = V_{DS}, I_D= 1mA
$\Delta V_{GS(th)}$	Change in $V_{GS(th)}$ with Temperature			-4.5	mV/°C	V_{GS} = V_{DS}, I_D= 1.0mA
I_{GSS}	Gate Body Leakage			100	nA	V_{GS} = ± 20V, V_{DS} = 0V
I_{DSS}	Zero Gate Voltage Drain Current			10	μA	V_{GS} = 0V, V_{DS} = Max Rating
				1.0	mA	V_{GS} = 0V, V_{DS} = 0.8 Max Rating T_A = 125°C
$I_{D(ON)}$	ON-State Drain Current	1.2	2.0		A	V_{GS} = 5.0V, V_{DS} = 25V
		3.0	6.0			V_{GS} = 10V, V_{DS} = 25V
$R_{DS(ON)}$	Static Drain-to-Source ON-State Resistance			15	Ω	V_{GS} = 3.0V, I_D = 250mA
			1.5	2.0		V_{GS} = 4.5V, I_D = 750mA
			1.0	1.5		V_{GS} = 10V, I_D = 750mA
$\Delta R_{DS(ON)}$	Change in $R_{DS(ON)}$ with Temperature			0.75	%/°C	V_{GS} = 10V, I_D = 750mA
G_{FS}	Forward Transconductance	0.4	0.8		℧	V_{DS} = 25V, I_D = 1.0A
C_{ISS}	Input Capacitance		70	125	pF	V_{GS} = 0V, V_{DS} = 25V f = 1 MHz
C_{OSS}	Common Source Output Capacitance		30	70		
C_{RSS}	Reverse Transfer Capacitance		15	25		
$t_{d(ON)}$	Turn-ON Delay Time			10	ns	V_{DD} = 25V, I_D = 1.5A, R_{GEN} = 25Ω
t_r	Rise Time			10		
$t_{d(OFF)}$	Turn-OFF Delay Time			20		
t_f	Fall Time			10		
V_{SD}	Diode Forward Voltage Drop			1.8	V	V_{GS} = 0V, I_{SD} = 1.5A
t_{rr}	Reverse Recovery Time		300		ns	V_{GS} = 0V, I_{SD} = 1.5A

Notes:
1. All D.C. parameters 100% tested at 25°C unless otherwise stated. (Pulse test: 300μs pulse, 2% duty cycle.)
2. All A.C. parameters sample tested.

Switching Waveforms and Test Circuit





Typical Performance Curves

Output Characteristics



Saturation Characteristics



Transconductance vs. Drain Current



Power Dissipation vs. Ambient Temperature



Maximum Rated Safe Operating Area



Thermal Response Characteristics



Typical Performance Curves

BV_{DSS} Variation with Temperature



On-Resistance vs. Drain Current



Transfer Characteristics



$V_{(th)}$ and R_{DS} Variation with Temperature



Capacitance vs. Drain-to-Source Voltage



Gate Drive Dynamic Characteristics



Supertex inc.
1235 Bordeaux Drive, Sunnyvale, CA 94089
TEL: (408) 744-0100 • FAX: (408) 222-4895
www.supertex.com